

## Single-Ended, Reflected-Type

BEAM 1224

## Conventional Beam Smoke Detectors

**General**

The System Sensor **BEAM1224** and **BEAM1224S** are four wire conventional projected beam smoke detectors. They are uniquely suited for protecting open areas with high ceilings where spot-type smoke detectors are difficult to install and maintain. **BEAM1224** and **BEAM1224S** are to be used with UL Listed compatible fire alarm control panels only. Installation of the single-ended reflective design is much quicker than a dual-ended projected beam detector. Alignment is easily accomplished with an optical sight and a two-digit signal strength meter incorporated into the beam detector. Listed for operation from -22°F to 131°F, the **BEAM1224** and **BEAM1224S** can be used in open area applications to provide early warning in environments where temperature extremes exceed the design limits for other types of smoke detection.

The **BEAM1224** and **BEAM1224S** are a transmitter/receiver unit and a reflector. When smoke enters the area between the unit and the reflector, it causes a reduction in the signal strength. When the smoke level (signal strength) reaches the predetermined threshold, an alarm is activated. The detectors have four standard sensitivity selections as well as two Acclimate™ settings. When either Acclimate™ setting is selected, the detector will automatically adjust its sensitivity using advanced software algorithms to select the optimum sensitivity for the specific environment.

The **BEAM1224S** has an integral sensitivity test feature of a filter attached to a servomotor inside the detector optics. Activation of the RTS451 remote test station moves the filter into the pathway of the light beam, testing the detector's sensitivity. This sensitivity test feature allows the user to quickly and easily meet the annual maintenance and test requirements of NFPA 72, without physical access to the detector

**Features**

- Transmitter/receiver built into same unit.
- Six user-selectable sensitivity levels.
- 16' to 328' (use BEAMLRK beyond 230') protection range.
- Removable plug-in terminal blocks.
- Digital display - no special tools required.
- Built-in automatic gain control compensates for signal deterioration from dust buildup.
- Optional remote test station.
- Optional long-range kit (BEAMLRK) for applications in excess of 230' (70 m).
- Optional multi-mount kit (BEAMMMK) providing ceiling or wall mount capability with increased angular adjustment.
- Optional heater kits (BEAMHK and BEAMHKR) for prevention of condensation (not intended to increase or reduce the specified operating temperature).

**Specifications****OPERATIONAL SPECIFICATIONS**

Protection range: 16 to 230 feet (5 to 70 m), 230 to 328 feet (70 to 100 m) using optional BEAMLRK kit.

Adjustment angle: ±10° horizontal and vertical. Note that the optics move independently of the unit.

**Sensitivity (6 levels):**

- Level 1 — 25%.
- Level 2 — 30%.
- Level 3 — 40%.
- Level 4 — 50%.
- Acclimate™ Level 5 — 30% to 50%.
- Acclimate™ Level 6 — 40% to 50%.

**Fault condition (trouble):**

- 96% or more obscuration blockage.
- In alignment mode.
- Improper initial alignment.
- Self-compensation limit reached.

**Alignment aid:**

- Optical gunsight.
- Integral signal strength indication.
- Two-digit display.

airflow characteristics, and response requirements. See NFPA 72.

#### **ENVIRONMENTAL SPECIFICATIONS**

**Temperature:** -22°F to 131°F (-30°C to 55°C).

#### **ELECTRICAL SPECIFICATIONS**

**Voltage:** 10.2 to 32 VDC (BEAM1224); 15 to 32 VDC (BEAM1224S).

**Standby current (24 VDC):** 17 mA maximum.

**Alarm current (24 VDC):** 38.5 mA maximum.

**Alignment mode current (24 VDC):** 28 mA maximum.

**Test mode current (BEAM1224S only):** 500 mA maximum @ peak test.

**Relay contacts:** 0.5 A @ 30 VDC.

**Reset time:** 0.3 seconds maximum.

**Start-up time (after 2 min. reset):** 60 seconds maximum.

**Alarm verification time:** 5 seconds maximum.

**Remote output (alarm or trouble):** Voltage: 15 to 32 VDC.

NOTE: Output voltage is the same as device input voltage.

**Current:** 15 mA maximum, 6 mA minimum. NOTE: Output current is limited by 2.2K ohm resistor.

**Heater kit BEAMHK:** **Voltage:** 15 to 32 V. **Current:** 92 mA maximum @ 32 V (heater only). **Power consumption:** nominal 1.6 W @ 24 V; maximum 3.0 W @ 32 V.

**Heater kit BEAMHKR:** **Voltage:** 15 to 32 V. **Current:** 450 mA maximum @ 32 V (per reflector). **Power consumption (perreflector):** nominal 7.7 W @ 24 V; maximum 15.0 W @ 32 V.

#### **MECHANICAL SPECIFICATIONS**

**Shipping weight:** 3.9 lbs (1.77 kg).

**Wiring:** plug-in terminal blocks, 12 to 22 AWG (3.1 to 0.33 mm<sup>2</sup>).

**Detector dimensions:** 10.0" H x 7.5" W x 3.3" D (254 mm H x 191 mm W x 84 mm D).

**Reflector dimensions for 16' to 230' (5 to 70 m)**

**applications:** 7.9" x 9.1" (200 x 230 mm).

**Reflector dimensions for applications beyond 230'/70 m:** 15.7" x 18.1" (400 x 460 mm).

#### **Agency Listings and Approvals**

These listings and approvals apply to the modules specified in this document. In some cases, certain modules or applications may not be listed by certain approval agencies, or listing may be in process.

Consult factory for latest listing status.

- **UL Listed:** S911
- **ULC Listed:** S911
- **MEA Listed:** 54-04-E
- **Maryland State Fire Marshal:** Permit # 2165
- **CSFM:** 7260-1653:168
- **FM Approved**

#### **Product Line Information**

**BEAM1224:** Conventional beam smoke detector.

**BEAM1224S:** Conventional beam smoke detector with integral sensitivity test.

**BEAMLRK:** Long range accessory kit (required for applications in excess of 230 ft/70 m).

**BEAMMMK:** Multi-mount kit (provides ceiling or wall mount capability with increased angular adjustment).

**BEAMSMK:** Surface-mount kit.

**RTS451:** Remote test station.

**RTS451KEY:** Remote test station with key lock.

**BEAMHK:** Heating kit for use with the transmitter/receiver unit of BEAM1224(S). For prevention of condensation.

**BEAMHRK:** Heating kit for use with the reflector of BEAM1224(S). For prevention of condensation.